

## OSTA 620



<b>CASE</b>	<ul style="list-style-type: none"> <li>▪ Step Advanced 2007 Mini Tower Micro Atx, 2x Fan 12cm (1 front, 1 rear)</li> <li>▪ 4x 5.25" External Units, 1x 3.5" External Units, 6x 3.5" External Units</li> <li>▪ 2x Usb 2.0, 1x Mic, 1x Spk</li> </ul>
<b>POWER</b>	<ul style="list-style-type: none"> <li>▪ 450W max</li> </ul>
<b>CPU</b>	<ul style="list-style-type: none"> <li>▪ Amd® Athlon 64bit X2 (Dual core) Am2 6000+ 3.0 GHz, FSB 2000 MHz 128Kb(x4) L1 cache, 512Kb(x2) L2 cache</li> </ul>
<b>MEMORY</b>	<ul style="list-style-type: none"> <li>▪ 1GB DDR2 667 MHz</li> </ul>
<b>HARD DISK</b>	<ul style="list-style-type: none"> <li>▪ 3.5", 320Gb SATA II 7200 rpm</li> </ul>
<b>VGA CARD</b>	<ul style="list-style-type: none"> <li>▪ Nvidia® Geforce 8400gs 256MB PciExpress</li> <li>▪ 1xDVI, 1xVGA, 1xTv-out(s-video)</li> </ul>
<b>MOTHERBOARD</b>	<ul style="list-style-type: none"> <li>▪ Gigabyte® M52s-s3p Am2</li> </ul>
<b>CHIPSET</b>	<ul style="list-style-type: none"> <li>▪ Nvidia® nForce 520</li> <li>▪ Super I/O chip : ITE IT8716</li> </ul>
<b>BIOS</b>	<ul style="list-style-type: none"> <li>▪ Award BIOS, 4MB</li> </ul>
<b>MEMORY SLOTS</b>	<ul style="list-style-type: none"> <li>▪ 4 Ddr2 DIMM slots, support up to 16 GB</li> <li>▪ Support dual channel Ddr2 800/667/533/400 Dimms</li> </ul>
<b>AUDIO</b>	<ul style="list-style-type: none"> <li>▪ Realtek ALC888 Audio codec</li> </ul>
<b>LAN</b>	<ul style="list-style-type: none"> <li>▪ Realtek RTL8111SC Gigabit Ethernet controller 10/100/1000Gb</li> </ul>
<b>I/O INTERNAL CONNECTOR</b>	<ul style="list-style-type: none"> <li>▪ 1x 24-pin ATX power connector, 1x 4-pin ATX 12V power connector</li> <li>▪ 1x floppy connector</li> <li>▪ 1x IDE connectors</li> <li>▪ 4x SATA 3Gb/s connectors</li> <li>▪ 1x CPU fan connector, 1x system fan connector</li> <li>▪ 1x front panel connector, 1x front audio connector</li> <li>▪ 1x CD In connector, 1x SPDIF In/Out connector</li> <li>▪ 3x USB 2.0/1.1 connectors for additional 6 USB 2.0/1.1 ports by cables</li> <li>▪ 1x Power LED connector, 1x Chassis Intrusion connector</li> </ul>
<b>EXPANSION SLOTS</b>	<ul style="list-style-type: none"> <li>▪ 1X Pci Express x16, 2x Pci Express x1, 4x Pci</li> </ul>
<b>I/O PORTS AND CONNECTORS</b>	<ul style="list-style-type: none"> <li>▪ 1x PS/2 keyboard port, 1x PS/2 mouse port</li> <li>▪ 1x coaxial S/PDIF Out port, 1x optical S/PDIF Out port</li> <li>▪ 4x USB 2.0/1.1 ports</li> <li>▪ 1x parallel port, 1x serial port</li> <li>▪ 1x RJ-45 port</li> <li>▪ 6x audio jacks</li> </ul>
<b>STORAGE PERIPHERAL</b>	<ul style="list-style-type: none"> <li>▪ Dvd Rw/Ram +/- 20x Dual Layer</li> <li>▪ 6in-1 Card Reader CF/SD/SC/MMC/MS black 3.5"</li> </ul>
<b>PERIPHERAL</b>	<ul style="list-style-type: none"> <li>▪ Optical mouse, Keyboard</li> </ul>
<b>WARRANTY</b>	<ul style="list-style-type: none"> <li>▪ 24 months on center</li> </ul>
<b>SOFTWARE</b>	<ul style="list-style-type: none"> <li>▪ Compatible with Windows 7/Vista (All version), Cd Driver</li> </ul>